



Party Premium Plus (lithium battery)

Article Number: 4955

Ca. 2,9 kg less weight and nearly 25% more flashes than the lead gel battery version!

The Party Premium Plus with an integrated radio receiver offers not only the possibility of radio controlled triggering but also provides the option of power adjustment in 1/10 f-stop increments. Even the modeling light can be switched on and off remotely. The channel can be selected easily by using the RC/CH button on the operator panel. In total, there are 3 different channels available on the device. On the receiver, the channel is selected by means of a sliding switch on the side. There you can also select an additional all-channel function, by means of which several devices can be controlled simultaneously. Shortest sync times of cameras can be used without restriction.

Thanks to the transmitter's low 6 V voltage, this system offers unquestionably the safest mode of operation, particularly in conjunction with digital cameras. It can connect either to the camera's direct X-contact or, using the sync cable provided, to the camera's sync socket. The Party's radio antenna is now screwed on and can be removed or replaced easily by the user, if needed. Another advantage of this technology: When working over great distances, a special longer antenna with considerably increased sensitivity (accessory) can be used. In response to the wishes of many of our costumers, the previous sync socket was replaced by a standard socket with a diameter of 6.3 mm. Thus all standard sync cables can be connected. The socket is protected against water drops by means of a seal plug.

Technical data

| | |
|---|---|
| Rated energy: | 1200 J |
| Aperture 100 ASA, t 1/60, 12" reflector, 1 m distance: | f 128 0/10 |
| Flash duration, t 0,5 | |
| 1 EH Pro Mini 1200P: | 1/1.200 s |
| 1 EH Pro Mini 1200P Speed: | 1/1.850 s |
| Charging time to 100%: | 2,7 s |
| Charging time to min. energy: | 0,4 s |
| Output adjustment flash energy: | 6 f |
| Output distribution: | asymmetrical |
| Flash sockets: | 2 (round sockets) |
| Built-in radio receivers: | Strobe Wizard Plus |
| Remote control: | Radio, output adj., modeling light, test, standby, synchronization |
| Weight: | ca. 6,0 kg |
| Dimensions (LxWxH): | 21 x 21,4 x 32,1 cm |

Technical data are subject to change. The listed values are guide values and should not be understood as binding in a legal sense. The values can differ due to tolerances in used components. Values attained at 230 V / 50 Hz voltage. Date of revision: August 2011