



Nova D 2400

Article number: 3624

- Metal housing with sturdy, protective rubber profile
- Special ergonomical handle bar for carrying, with integrated spare fuses
- Multivoltage (110 – 240 V) high performance mains switch
- Extremely fast flash recycle times 0,35 - 1,1 s
- Extremely short flash duration up to 1/4.500 s (t 0,5 with Speed Head, D 1200)
- Choice of symmetric or asymmetric power distribution via the „A“ or „B“ socket.
- Individual settings in 1/10 f-stop increments
- Integrated Profoto Air radio, Hensel Strobe Wizard Plus and freemask receiver, switchable
Radio remote functions: output adjustment, triggering, modelling light, standby. Full remote control with both systems, manufacturer compatible.
- Integrated radio antenna for optimum protection
- Output adjustment in 1/10 f-stop increments
- Output range of 8 f-stops
- Large 7-segment performance indicator
- Active cooling due to extremely quiet fan
- Connector socket for round plugs / Pro Mini / 20-pol. long plug via adapter
- USB port for software updates
- Durable foil surface with ‚real‘ push-buttons for ‚feel good‘ use
- New foil surface with clearly detectable imprint around the push-buttons. Optimal for your sense of touch
- Hensel usage concept – name and position of switches and control units are generally the same. Working without rethinking!

- APD, internal power reduction when reducing power output
- Built-in photocell , seperately switchable
- Synchronous socket for standard cord 6,3 mm
- Test button for manual test firing
- Very low synchronous voltage protects digital cameras
- Thermal monitoring of performance electronics

Technical data

Rated energy:	2400 J
Aperture 100 ASA, t 1/60, 12" reflector, 1 m distance:	f 180 0/10
Flash duration, t 0,5	
1 EH Pro Mini 1200P:	1/1.450 s
1 EH Pro Mini 1200P Speed:	1/3.160 s
Charging time to 100%:	0,35 s
Charging time to min. energy:	1,1 s
Output adjustment flash energy:	8 f
Output distribution:	symmetrical or asymmetrical
Flash sockets:	2 (round sockets)
Built-in radio receivers:	Strobe Wizard Plus / freemask Profoto Air
Remote control:	Radio, output adj., modeling light, test, standby, synchronization
Weight:	7,8 kg
Dimensions (LxWxH):	26 x 19,5 x 28,3 cm

Technical data are subject to change. The listed values are guide values and should not be understood as binding in a legal sense. The values can differ due to tolerances in used components. Values attained at 230 V / 50 Hz voltage. Date of revision: August 2011